

THE MOUSE VALVE SERIES EV, ET, EC SERIES VALVES

Clipparo Minimatic

Like a mouse, this valve is quiet, quick, eats very little (0.67 watts) and is cute. Valves accept low voltage, low current signals, convert them into high pressure (100 psig) pneumatic outputs. Optional low pressure/medium flow and low pressure/high flow are available. (The air supply should be reasonably clean and dry for optimum performance. Recommended filtration is 40 micron.)



Clippard Minimatic electronic valves are precision-built 2-way or 3-way control valves, utilizing a unique, patented, valving principle. There are no sliding parts. Complete poppet travel is a mere 0.007". As a result, low power consumption and exceptionally long life are major benefits of this design.

The valves are very quiet in operation and also very cool. No flow is needed for cooling. The valves' small size makes them well suited to a wide range of applications in biomedical, EDP, environmental test equipment, textile machines, packaging machinery, computerized industrial automation, and portable systems.





Clippard Functional Simplicity



- The design of Clippard electronic valves is a deceptively simple arrangement with a minimum of operating parts, and remarkably straight forward low power operation.
- The Clippard "spider" is the only moving part and its motion to operate the value is a mere 0.007" travel.
- Low voltage D.C. inputs, signals from simple manual switching up to computer directed systems, move the spider in extremely fast response time... 5-10 milliseconds.
- The unit uses extremely low power (0.67 watts at the rated voltage) and is cool running. The valves are light in weight, compact in physical size and mount easily in space-saving packages.

Quick Connect

Clippard ET valves feature spade lugs for simple, quick secure low voltage connections. Wire crimp-on spade lug connectors are available separately to adapt electronic wiring where necessary. Clippard original EV type



valves are available in popular voltages with 18" wire leads. The EC model utilizes a 0.025" square pin connector.

Easy Mount

The complete line of EC, EV, and ET electronic valves are available #1 with two mounting options. Standard base



models have two 6-32 threaded, 7/32" deep mounting holes. Manifold models are equipped with a bottom stud, 5/32" long with #10-32 thread, which fits Clippard standard and special manifolds, accessory valves and subplates. Spanner holes in the valve body permit tightening.

	NOMINAL		Working Range	
Voltage	Current (amps)	Resistance (ohms)	Power (watts)	(cont. duty)
6	0.11	54	0.67	
12	0.055	218	0.67	90% - 150% of rated voltage
24	0.028	864	0.67	5

THE MOUSE VALVE SERIES EV, ET, EC Series Valves



Accessories



EVB-2 & EVB-3 Booster

Clippard EVB-2 & EVB-3 booster valves mate with manifold mount EC, EV, and ET valves and manifolds to provide increased flow. Direct piloting from a Clippard EC, EV and ET valve provides a flow of up to 6.1 SCFM at 100 psig.

2020/2021 High Flow Valves

Model 2020 and 2021 high flow valves are piloted 3-way valves that work with the Clippard EC, EV, and ET 3-way manifold valves. Output from the EC, EV, or ET will actuate the valve and produce output up to 22 SCFM at 100 psig. Piloted 4-way valves are also available as R-481 and R-482.





Dual Supply Manifold

Shown is the 15490-3 Clippard Dual Supply Manifold with two ET-3M electronic/pneumatic interface valves. 1/8" NPT inlet is seen at the left of the manifold with the dual #10-32 port outlets at the right.

Multi-Valve Manifolds

Multi-valve manifolds are available in two lengths with either single or double (top or top and bottom) rows of outputs for versatility in application. Input to all valves mounted on this manifold is through the manifold end. Outputs are individual #10-32 ports for hose barb fittings and vinyl or urethane hose.





Pilot Manifold

Here a Clippard ET valve is mounted to the 15491-1 Clippard Pilot manifold, making it possible for the ET-3M valve controlled by an electronic signal to actuate a larger air-piloted valve or an air cylinder.









		Type: Normally Closed 2- or 3-Way
	exhaust (3-way only)	Medium: Air (40 micron filtration)
		Temperature Range: 30° to 180°F
All second secon		Power Consumption: 0.67 watt
		Response: 5 - 10 milliseconds
	1.560	Mounting: Manifold
EC-2M- 0		Ports: Manifold mounted with #10-32 stud
	0. <u>158</u>	Operating Range: 90% to 150% of rated voltage
		Air Flow: 0.6 scfm @ 100 psig;
	#10-32 thd outlet	17 I/min @ 7 bar "L" option - 0.5 scfm @ 50 psig; 14 I/min @ 3.5 bar "H" option - 0.45 scfm @ 25 psig;
		13 l/min @ 1.8 bar Pressure Range:
		28" Hg Vac. to 105 psig
ET-2M- 0 ET-3M- 0		28" Hg Vac. to 50 psig
24 VDC	1.187	"H" option:
EV - 🗆 M - 🗅 - 🖵		
EV-2M- 24 VDC	#10-32 thd. inlet 0.875	For Cable and Connectors, see Page 187.
NUMBERING SYSTEM		
E - Connector T - Terminal Spades V - Wire Leads E - D M 2 - 2-Way 3 - 3-Way	 Standard Options: Blank - Standard orifice (50 H - 0.040 orifice (25 V - Fluorocarbon sea Voltages: * 6 - 6 Volts 12 - 12 Volts 24 - 24 Volts Standard Options: Blank - Standard Options: Blank - Standard Options: Blank - Standard Options: Blank - Standard Options: E - EPR seals S - Silicon seals D - Diode 	* Consult factory for availability of non- psig max) psig max) and other options ns:









EV, ET, EC SERIES 3-WAY FULLY PORTED VALVES MANIFOLD MOUNT



Clippard

Minimatic'









Note: Supply pressure must be applied to both ports 1 & 4. Minimum pressure on port 4 should be 40 psig.

R-482-□

ppare

linimatik

R-481-🗅

For more information please see page 260 in the Modular Valve section of this catalog.





Note: Supply pressure must be applied to both ports 1 & 4. Minimum pressure on port 4 should be 40 psig.

Type: 4-way combination electronic and modular spool type interface valve. Fully ported ET-3 & R401 hybrid

Clippard Minimatic

Medium: Air, water, or oil; pilot - air only

Input Pressure: Pilot - 40 psig minimum Working - 0-150 psig

Air Flow: Valve - 9 scfm @ 100 psig

Voltages: R-481-6 6 VDC R-481-12 12 VDC R-481-24 24 VDC

Mounting: Uses Octoport base and two captivated screws

Ports: Valve has patented Octoport system

Type: 4-way combination electronic and modular spool type interface valve. Fully ported ET-3 & R402 hybrid

Medium: Air, water, or oil; pilot - air only

Input Pressure: Pilot - 40 psig minimum Working - 0 to 150 psig

Air Flow: Valve - 9 scfm @ 100 psig

Voltages: R-482-6 6 VDC R-482-12 12 VDC R-482-24 24 VDC

Mounting: Uses Octoport base and two captivated screws

Ports: Valve has patented Octoport system



Black molded lug connectors are available for easy push on connection ET-C48 is 48" in length, ET-C120 is 120" in length

EC/ECO and EI/EIO valves



3831

Insulated crimp-on spade lug connectors are available for wiring up leads to connect electronic circuit to ET style valves. Accepts #22, #24, or #26 wire







EVB-2

EC, EV and ET Piloted 2-Way Valve, Manifold Mount

Electronic Valve Booster Amplifies the flow capacity of EC, EV and ET type valves by over twelve times. Manifold style electronic valves mount onto booster body, which, in turn, mounts on Clippard manifolds.





Type: 2-Way Normally Closed, Pressure Piloted Valve

Medium: Air

Input Pressure: 20 to 150 psig

Air Flow: 6.1 scfm @ 100 psig

Response: 20 milliseconds at 20 psig 13 milliseconds at 100 psig

Mounting: Mounts to manifold

Ports: Inlet and outlet through manifold

Materials: Nickel plated brass, acetyl, stainless steel and Buna-N

Additional Note Use only normally closed 3-way pilot valves in conjunction with EVB-2

EVB-3

EC, EV and ET Piloted 3-Way Valve, Manifold Mount

Electronic Valve Booster Amplifies the flow capacity of EC, EV and ET type valves by over twelve times. Manifold style electronic valves mount onto booster body, which, in turn, mounts on Clippard manifolds.





Type: 3-Way Normally Closed, Pressure Piloted Valve

Medium: Air

Input Pressure: 20 to 150 psig

Air Flow: 6.1 scfm @ 100 psig

Response: 20 milliseconds at 20 psig 13 milliseconds at 100 psig

Mounting: Mounts to manifold

Ports: Inlet and outlet through manifold

Materials: Nickel plated brass, acetyl, stainless steel and Buna-N

2013 - 🗆

Electronic Fluidamp

Low-power DC solenoid solid state output signals can be directly converted to high pressure pneumatic power without amplification



Type: 3-Way Normally Closed, Electronic Valve

Medium: Air

Additional Note Use only normally closed 3-way pilot valves in conjunction with EVB-3

Input Pressure: 30 to 100 psig

Air Flow: 22 scfm @ 100 psig

Bleed Flow: 0.10 scfm @ 100 psig

Filtration: 10 micron

Frequency Response: 50 Hz @ 100 psig 70 Hz @ 30 psig

Ports: 1/8" NPT female Switching Speed: 10 milliseconds

Electrical Data

Continuous Overload: 350% @ 25°C ambient 250% @ 50°C ambient Power Consumption: Less than .50 watts at rated voltage (80 ma. @ 6V, 40 ma. @ 12 V, 20 ma. @ 24V) Leads: 28 gauge stranded P.V.C. insulated Standard Options: 2013-6 6 volts DC 12 volts DC

2013-12

2013-24 24 volts DC



EV, ET, EC SERIES ACCESSORIES



Type: 3-Way Normally Closed, Pressure

Piloted Valve

Medium: Air

2020/2021

High Flow EC, EV and ET Piloted 3-Way Valves

Designed to be piloted by a Clippard EC, EV and ET manifold mount electronic valve. Output from the EC, EV and ET actuates the valve to produce outputs up to 22 scfm at 100 psig. Combines low wattage, long life and cool running of the EC, EV and ET valves with quick response and high flow of Clippard "Fluidamp" type valves. The 2020 and 2021 are identical in all respects except one. The 2020 has an external #10-32 port for the pressure supply to the EC, EV, and ET electronic pilot valve.



Clippard Instrument Laboratory, Inc. 877-245-6247 www.clippard.com



EV, ET, EC Series Manifolds



Multi-Valve Manifolds

Construction: Black anodized aluminum



	# of		
Order No.	Valves	"A"	"B"
15481-4	4	1.875″	3.750″
15481-4-M5	4	42.6 mm	95.3 mm
15481-6	6	3.750″	5.625″
15481-6-M5	6	95.3 mm	142.9 mm



Eight ET valves mounted on a 15482-8

15481-2 & 15481-2-M5 (Metric)

Mounts two valves on one side only



15481-4 & 15481-4-M5 (Metric)

15481-6 & 15481-6-M5 (Metric) Mounts six valves on one side only #10-32 (M5) x 3/16" deep mounting holes 0.625 (15.9) 4 ⊷0.937-(23.8) A В 1/8" NPT (G1/8) manifold inlet port (both ends) 0.937 0.411 (11.3) #10-32 (M5) valve inlet ports (23.8) valve outlet ports 0.875 0.156 (39.6) #10-32 (M5) manifold outlet ports

15482-8 & 15482-8-M5 (Metric)

Mounts eight valves, four each on opposite sides



15482-12 & 15482-12-M5 (Metric)

Mounts twelve valves, six each on opposite sides











EMC-08-00-01 and EMC-12-00-01 are part numbers for cards without any valves, and without manifold. Manifold mounting hardware is included. Manifolds may be ordered separately, if desired.

Part numbers are: 15482-8 and 15482-12

Convenience in interfacing electronics and pneumatics... fast mounting, completely assembled, manifolded valve cards.

Clippard Electronic Manifold Cards

Now you can direct low-voltage DC signals from controllers, systems, computers or other sources to operate powerful pneumatic valves with a minimum of piping and hook-up.

Self-contained card includes:

- 8 or 12 Clippard ET interface valves
- Manifold mount for single air supply
- Circuit board fully wired
- Instant plug-in with 25-pin connector
- Resistor, diode, LED and switch for each valve
- Auxiliary power supply connection

Ready to operate quickly. Just mount the card and make external connection.

And each valve may be individually removed and replaced without any need for desoldering!

Features

- Fast, easy to mount
- Pre-assembled; all valves mounted

EMC Cards

Minimatic

- 8 or 12 valve sizes
- 6, 12 or 24 volts DC
- Low power requirements (0.67 watt per valve)
- Choice of valve types
- Each valve switchable
- Shut-off spike protection
- 25-pin connector
- No expensive card rack required



Auxiliary Power Input

Power to operate the valves may be provided through two sources: ONE, through the 25-pin connector if your signal source also has sufficient power to operate the bank of valves, or TWO, through a separate auxiliary power input connection built into the board. To isolate power from the 25-pin connector, use the power source selector switch.

NOTE: In applying power on a temporary basis, use care to observe proper circuit polarity.

C

C

Power Selector Switch

Two-position selector switch enables choice of power input source (25-pin connector or auxiliary).

25-Pin Connector

Reverse Polarity Protection Circuit using diodes and capacitor

Circuit using diodes and capacitor provides input voltage protection against reverse polarity.

Resistor-Diode-LED Circuit

Individual circuit to each valve provides protection against shut-off spikes. LED is illuminated when valve is actuated.

Clippard Electronic Valves

Valve Connection Cords

Cord and plug leads are terminated with solder connections on the board, and connect by molded plug to the valves. All connections are completed at the factory.

Clippard Valve Manifold Compact, efficient mounting of the

Compact, efficient mounting of the valves is by Clippard multi-valve manifolds.

Mounting Holes Four (EMC-08) and six (EMC-12) mounting holes 0.191" dia. are built into each board.

LED Bank Illuminated LED signals that the valve is actuated.

3-Position Detented Switches

Three position slide switch provides for: ON - Power "ON"; valve is activated OFF - Power "OFF"; valve not connected CONN - Valve connected to 25-pin connector, and will be controlled through it.

Valve Identification

Valve numbers are silk-screened on each panel.

Printed Circuit Board Durable laminated fiberglass



